

# Integrated WizarSwitch

## IPC-8+



**With  
Built-in  
HDMI Selector  
and Splitter Functions!**

**comm Integrated WizarSwitch (IPC Series)** - Designed to control your Audiovisual Equipment in the most simplified ways via RS-232 commands; reasonably priced and works with most projectors and plasma displays.

One Touch Selection with LED Back-Lit Indications on the selectors' buttons, you can easily control your displays with its various selector buttons (e.g. select the different input source, volume and/or screen controls etc)

### Built-In HDMI Selector and Splitters Functions.

Widely used in Classrooms, Auditoriums, Lecture Theatres, Conference Rooms etc.

## FEATURES

**Display Controller** for your Projector, Plasma (Power ON/OFF, input source selections, volume control) via RS232 Commands

**One Touch Selection** with LED Back-Lit Indications

**INPUTS : 2 HDMI, 3 USB, 1 VGA**

**OUTPUTS: 2 HDMI, 2 USB, 1 VGA**

**Digital Volume Control** for sound level adjustments

**Volume Control Knob** for MIC Inputs sound adjustments

### NEW Features!

- **STANDBY mode - MIC Volume Control usable**
- **HDMI1 with Audio: PC Monitor is usable even when Projector is OFF**
- **3 USB Connections**

### SELECTOR SWITCH

(with LED Back-Lit Indications)

- Display ON / OFF
- FUNCTION (Blank / Sync)
- Screen / Audio Volume (UP / DOWN)
- Screen / Audio IN Selector
- HDMI 1 / USB 1 IN Selector
- HDMI 2 / USB 2 IN Selector
- PC / USB 2/ WIRELESS Selector
- RESET for HDMI

## SPECIFICATIONS

### A) Input

- |               |                               |
|---------------|-------------------------------|
| HDMI 1 / 2    | - HDMI with Audio Embedded    |
| PC Signal     | - VGA (D-Sub 15-Pin Female)   |
| PC Audio      | - 3.5mm Mini Jack             |
| Microphone IN | - 3.5mm Mini Jack             |
| USB 1 / 2 IN  | - USB Female Type B Connector |
| USB IN        | - USB Female Type A Connector |

### B) Output

- |                |               |
|----------------|---------------|
| HDMI           | - HDMI        |
| HDMI           | - Monitor OUT |
| PC Signal      |               |
| Audio Signal   |               |
| Microphone OUT |               |

### C) Communication Control

- |                     |                              |
|---------------------|------------------------------|
| Serial Control Port | - RS232                      |
| Baud Rate           | - 9600, 19200, 38400, 115200 |
| Data / Stop Bits    | - 8 Bits / 1 Bits            |
|                     | No parity                    |

### D) Power

- |                      |  |
|----------------------|--|
| DC 12V Power Adapter |  |
|----------------------|--|

All products information and specifications are subject to changes without prior notice.